

# PACKAGE CONFIGURATIONS

## 153 Ball Pin Configuration

Pin NO	Name
A3	DAT0
A4	DAT1
A5	DAT2
B2	DAT3
B3	DAT4
B4	DAT5
B5	DAT6
B6	DAT7
K5	RSTN
C6	V <sub>CCQ</sub>
M4	V <sub>CCQ</sub>
N4	V <sub>CCQ</sub>
P3	V <sub>CCQ</sub>
P5	V <sub>CCQ</sub>
E6	V <sub>CC</sub>
F5	V <sub>CC</sub>
J10	V <sub>CC</sub>
K9	V <sub>CC</sub>
C2	V <sub>DDI</sub>
M5	CMD
H5	Data Strobe
M6	CLK
J5	V <sub>SS</sub>
A6	V <sub>SS</sub>
C4	V <sub>SS</sub>
E7	V <sub>SS</sub>
G5	V <sub>SS</sub>
H10	V <sub>SS</sub>
K8	V <sub>SS</sub>
N2	V <sub>SS</sub>
N5	V <sub>SS</sub>
P4	V <sub>SS</sub>
P6	V <sub>SS</sub>

Ball-side down view

○ — NC

